



### ASSEMBLY OF 22'-0" POINT RAIL

RIGHT HAND POINT RAIL - GTS 328 A

LEFT HAND POINT RAIL - GTS 328 B (ILLUSTRATED)

POINT ASSEMBLY INCLUDES:

ITEM NO.	DESCRIPTION	STANDARD PLAN NO.	QUANTITY	
			DWG. No. GTS-0328 A	B
1	RIGHT POINT RAIL LEFT POINT RAIL	R11C-506.1 R11C-506.1	1 -	- 1
2	REINFORCING BAR 1/2" THK. X 19'-0" LONG	GTS-0342/H	2	2
3	STOP BLOCK No. 1	GTS-0339/K	1	1
4	STOP BLOCK No. 2	GTS-0339/L	1	1
5	3/4" DIA-10 UNC SQ. HD. BOLT x 4" LG. C/W SQ. NUT	GTS-1305/6	4	4
6	1" DIA-8 UNC SQ. HD. BOLT x 3-1/2" LG. C/W SQ. NUT	GTS-1309/13	17	17
7	SPRING WASHER FOR 3/4" DIA. BOLT	GTS-1301	4	4
8	SPRING WASHER FOR 1" DIA. BOLT	GTS-1301	17	17
9	3/16" COTTER PIN X 1-1/4" LONG		4	4

### NOTES:

-SWITCH CLIPS ARE NOT INCLUDED IN SWITCH POINT ASSEMBLY AND MUST BE ORDERED SEPARATELY IF REQUIRED.

-WHEN REFERRING TO POINT RAILS, DRAWING No. MUST BE STATED AS A OR B TO INDICATE RIGHT OR LEFT HAND POINT:

- A - RIGHT HAND POINT
- B - LEFT HAND POINT (ILLUSTRATED)

NOTE: THE FOLLOWING ITEMS ARE NOT INCLUDED IN THE SWITCH POINT ASSEMBLY AND MUST BE ORDERED SEPARATELY IF REQUIRED.

ITEM NO.	DESCRIPTION	STANDARD PLAN NO.	QUANTITY	
			DWG. No. GTS-0328 A	B
10/11	<u>SIDE JAW CLIPS</u> SWITCH CLIP - RIGHT HAND (338 A-2) SWITCH CLIP - LEFT HAND (338 B-2)	GTS-0338/3 GTS-0338/4	3 -	- 3
	<u>MJS CLIPS</u>			
10	MJS CLIP ASSEMBLY (352C)	GTS-0352/C	1	1
11	MJS CLIP ASSEMBLY (352D)	GTS-0352/D	2	2

**METRIC CONVERSION: 1 inch=25.4mm, 1 foot=304.8mm**

1	18/07/27	ADDED IMPERIAL TO METRIC CONVERSION NOTE	
No.	Date	Revision	By Approved
Standard/		<b>ASSEMBLY 22'0" POINT RAIL FOR POWER GENERATION 115 LB. R.E. RAIL</b>	
Drawn	GGS	Checked	GWM
		Approved	<i>[Signature]</i> VP Engineering & Asset Management
Date	SEPT 15/2017	Plan Number	GTS-0328
		Rev	1
REFERENCE: TS-0328_R2		Sheet 1 OF 1	